

INSTALLATION INSTRUCTIONS

110V 30W LED GLOBE LIGHT MODELS: GLS30YPW, GLE30YPW

INTRODUCTION

The 110V 30W Globe Light is designed with portability and usability in mind. With its 360 degree light output and various mounting options, it is the perfect way to light a work site without taking up too much space. It comes complete with a mounting hook option on the bottom, it is powered by the 5M arctic cable with 16A 110V plug and has a 16A 110V built in socket to plug additional products into.



BOX CONTENTS

1 x Globe Light

SPECIFICATION



86lm/W

*Lumen output in emergency mode

Dimensions: L: 252 x Diameter: 190mm

Finish: Opal diffuser & yellow ABS body

LED: 60/75pcs of SMD 2835

Working Temperature: -20°C - 40°C (0°C - 40°C for emergency version)

H05VV-F 5m Cable included

PG11 Cable Glands included

Tripod available to order separately

SAFETY WARNING

- The installation should be carried out by a qualified electrician in compliance with the current edition of the IEE Wiring Regulations.
- Prior to installation, carry out the necessary risk assessment considering the people who could be at risk, the level of risk and the precautions required to control the risk
- Ensure that the circuit supply is isolated either by the circuit supply fuse being removed or the applicable circuit breaker being turned off before installation or any maintenance.
- Check the total load on the circuit ensuring the luminaire does not exceed the rating of the circuit cable, fuse or circuit breaker.
- If the fitting incorporates control gear, ensure careful sizing to avoid instances of nuisance tripping of the protective device used in the installation.
- Follow the provided installation instructions, using the fixings supplied or recommended.



Red Arrow Trading Ltd
Elsworth House, Herries Road South
Sheffield, S6 1QS

Tel: 0800 195 0006 **Fax:** 0870 195 0006

Email: sales@redarrowtrading.com **Web:** www.redarrowtrading.com

INSTALLATION INSTRUCTIONS

110V 30W LED GLOBE LIGHT MODELS: GLS30YPW, GLE30YPW

INSTALLATION INSTRUCTIONS

1. The 30W LED Globe Light is for use with 110V supply only.
2. Remove the globe light from the box.
3. The light has three mounting options (stand-alone, tripod and hanging hook) if required, the tripod can be purchased separately.
4. Attach the 110V plug to a suitable power source and test to see if the light is working.
5. If the emergency option has been selected, then the switch on the side must be in the 'ON' position. To charge the battery on the emergency version, the 30W LED Globe Light must be left connected and powered on. This will then begin to charge, the longer it is left connected, the longer the emergency light will last. (E.g. 24 hours charge will give 3 hours run time).
6. If you remove power from the 30W LED Globe Light and do not wish to have it running in emergency, then you can switch into the 'OFF' position. Please remember to put the switch back to the 'ON' position, before using again.
7. The 30W LED Globe Light can also have further ones attached to it, maximum number of lights is 20.

GUARANTEE

This product is guaranteed for a period of 2 years from the date of purchase. The guarantee is invalid in the case of improper use, tampering, removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the I.E.E. Wiring Regulations (BS7671).

The guarantee is also invalidated if the luminaire has been Mega tested. Should this product fail during the guarantee period it will be replaced free of charge, subject to correct installation and return of the faulty unit. We do not accept responsibility for any installation costs associated with the replacement of this product. Your statutory rights are not affected. We reserve the right to alter specifications without prior notice.

MAINTENANCE

- This fitting will require routine cleaning if used in adverse (dust, paint, welding, oils etc) environments.
- When this fitting comes to the end of its life or you choose to replace it, please do not dispose of it with your normal household waste. Please recycle where the facilities exist, check with your local authority or retailer for suitable options.



Red Arrow Trading Ltd
Elsworth House, Herries Road South
Sheffield, S6 1QS

Tel: 0800 195 0006 **Fax:** 0870 195 0006

Email: sales@redarrowtrading.com **Web:** www.redarrowtrading.com