

KOHLER®



DIESEL 10 LC A SILENCE AVR C5

PORTABLE POWER

GENERATING SET Range DIESEL SILENCE

PRODUCT ADVANTAGES

Generating set guaranteed 3 years
 KOHLER water-cooled industrial engine
 Very Silent
 Soundproofing and against shocks panels
 Hydrocarbons bulk tank

GENERATOR SMART CARE is a Bluetooth box which can be used on all the brand's portable generators.

TECHNOLOGY EQUIPPED WITH AN INNOVATIVE APPLICATION Generator Smart Care is a digital solution which provides access to:

- The list of generators
- The maintenance due dates
- A maintenance aid
- The map of reseller partners

The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature

Range DIESEL SILENCE

Both long run times and very long life for professional applications.

DIESEL 10 LC A SILENCE AVR C5

GENERAL SPECIFICATIONS

Range	DIESEL SILENCE
Frequency (Hz)	50 Hz
Max power (kW)	8.3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	27
75% cons. (l/h)	2.6
75% Autonomy (h)	10.4
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	79
Acoustic pressure level @7m in dB(A)	66

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	KDW702
Engine Type	Diesel O.H.V.
Start	Electrical
Oil shutdown	OUI
Displacement (cm3)	686
Oil system capacity including filters (l)	1.6

ALTERNATOR SPECIFICATION

Technology	Collar and brush
AVR Regulation	Yes
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + emergency stop button + hour meter + indicator + APM202

DIMENSIONS AND WEIGHT

Length (cm)	121.1
Width (cm)	79
Height (cm)	105.6
Dry Weight (kg)	310

PACKAGING

Packaging type	Box
Length (cm)	122.2
Width (cm)	80.4
Height (cm)	105.6
Weight (kg)	316
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



KOHLER®

\$DATEJOURS

DIESEL 10 LC A SILENCE AVR C5 - PORTABLE POWER – GENERATING SET DIESEL SILENCE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED

User and maintenance manual
Lifting eye
Battery without maintenance
Hour meter

OPTIONS

- R02B** This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker
- 3499231002834** RSTART2 - Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)
- 3499231001110** VERSO50 - Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger
- R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut
- RKB6** RKB6
- 3499231004678** RKDS6 - Maintenance kit for KOHLER KDW702
- RAP**
- RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable