



PERFORM 7500 T C5

PORTABLE POWER

GENERATING SETRangePERFORM

PRODUCT ADVANTAGES

Compact frame with protection panels against shocks

Starting up facilitated thanks to the summer/winter positions KOHLER air-cooled industrial engine Good value for money Generating set guaranteed 3 years

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

OVERSIZED ALTERNATOR The oversized alternator is ideal for supplying electronic equipment and secures the engines sypplying . It has very low harmonic current and limits the voltage and frequency variation of the power supplied as well as handling high surge loads.

Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



















PERFORM 7500 T C5

GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW)	6.5
Max power (kVA)	8.1
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	7.3
75% cons. (I/h)	2.6
75% Autonomy (h)	2.8
Sound power level guaranteed LwA dB(A)	99
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH440_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	429
Oil system capacity including filters (I)	1.3

ALTERNATOR SPECIFICATION

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55.5
Height (cm)	59
Dry Weight (kg)	93.5

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56.5
Height (cm)	60
Weight (kg)	95.5
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	583







ACCESSORIES SUPPLIED

Funnel
User and maintenance manual
Floor maintaining slot
Ergonomic handle grip

OPTIONS

NUS SEL INCIDUES THE HOUI THELE AND THE CHIEFERITIAL CITCUIT DIEAK	R03	This set includes the hour meter and the differential circuit breakers	r
--	-----	--	---

0

3499231920039 RKS2 - Maintenance kit for KOHLER CH395 and CH440 engines

RH1 Cover for SDMO 's generating sets, welding sets and water pumps

RPM Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x

32A/230 V and 1 x 16A/400V

RPQ For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10

mm² cable

RBAC Removable storage box

3499231000786 RLIFT2 - Central lifting yoke

3499231004555 GSC

RRB5 RRB5

