

PETROL INVERTER GENERATOR 3.8kW



FEATURES

- Powered by the latest EURO V emission standard, Senci SC230 petrol engine.
- Electric, recoil and remote key fob start
- Advanced inverter technology for sensitive equipment.
- Indicator for output, low oil & overload alert.
- ECO mode to regulate the engine speed and adjust fuel consumption.
- Thermal breaker protects from overload.
- 3 in 1 display for Voltage, Frequency and Hours.
- Automatic choke for cold start.
- Fuel shut-off valve prevents carburettor contamination during storage.

SPECIFICATIONS

PEAK OUTPUT	3800W
MAX. OUTPUT	3800W
CONTINUOUS OUTPUT	3500W
FUEL TYPE	Petrol
RUN TIME AT 50% LOAD	8.5h
OUTLETS	2 x 230V 13A, 1 x 12V 8A DC, 1 x 1.5A USB
FUEL TANK CAPACITY	10L
FREQUENCY	50Hz
LENGTH	585mm
WIDTH	485mm
HEIGHT	550mm
WEIGHT	52.00kg
NOISE LEVEL	62dB(A) @ 7m
STARTING METHOD	RECOIL, ELECTRIC & REMOTE
AVR (AUTOMATIC VOLTAGE REGULATOR)	N/A