

DUAL FUEL INVERTER GENERATOR 3.2kW



FEATURES

- Powered by the latest EURO V standard, easy-to-start Senci single-cylinder petrol engine.
- Smoothed output of <3% THD for running some sensitive appliances.
- Ultra-light and portable with a reduced weight of 24kg for easier transport with carry handle.
- ECO mode automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction.
- Low oil and power overload shutdown.
- Output indicator LED and display for voltage, frequency and run time.
- Large 6L fuel tank for up to 5.5 hours run time (petrol).
- Dual fuel usage on either petrol or LPG.

SPECIFICATIONS

PEAK OUTPUT	3200W (Petrol) / 3000W (LPG)
MAX. OUTPUT	3200W (Petrol) / 3000W (LPG)
CONTINUOUS OUTPUT	3000W (Petrol) / 2700W (LPG)
FUEL TYPE	Petrol / LPG
RUN TIME AT 50% LOAD	5.5h (Petrol)
OUTLETS	2 x 230V 13A, 1 x 5V USB
FUEL TANK CAPACITY	6.0L
FREQUENCY	50Hz
LENGTH	500mm
WIDTH	300mm
HEIGHT	440mm
WEIGHT	24kg
NOISE LEVEL	60dB(A) @ 7m
STARTING METHOD	RECOIL
AVR (AUTOMATIC VOLTAGE REGULATOR)	No

