

DUAL FUEL INVERTER GENERATOR 6.0kW



FEATURES

- Powered by the latest EURO V emission standard, Senci 320cc dual fuel engine.
- Electric and recoil start..
- Advanced inverter technology for sensitive equipment.
- Indicator for output, low oil & overload alert.
- ECO mode to regulate the engine speed and adjust fuel consumption.
- Thermal breaker protects from overload.
- 3 in 1 display for Voltage, Frequency and Hours.
- Automatic throttle for efficiency & lower noise output.
- Dual fuel usage on either petrol or LPG.
- Integrated wheel kit and pull-out handle for easier manoeuvrability

SPECIFICATIONS

PEAK OUTPUT	6000W (Petrol) / 5500W (LPG)
MAX. OUTPUT	6000W (Petrol) / 5500W (LPG)
CONTINUOUS OUTPUT	5500W (Petrol) / 5000W (LPG)
FUEL TYPE	Petrol / LPG
RUN TIME AT 50% LOAD	11h (Petrol)
OUTLETS	1 x 230V 32A, 1 x 230V 13A, 1 x 12V 8A DC, 1 x 5V USB
FUEL TANK CAPACITY	13.5L
FREQUENCY	50Hz
LENGTH	600mm
WIDTH	500mm
HEIGHT	540mm
WEIGHT	59kg
NOISE LEVEL	64dB(A) @ 7m
STARTING METHOD	ELECTRIC / RECOIL
AVR (AUTOMATIC VOLTAGE REGULATOR)	No

