

Generating Set

GE 5000 HBM - Petrol

Key Features

- Manual recoil
- Sockets: 2 x 230V 16A
- Overload thermal shut off
- Battery charger 12V c.c with fuse protection
- Protective frame
- Silenced
- Portable
- Meets EC directives for noise and safety

A.C. Generation - 50Hz - Single Phase, Brushless Alternator

Output *	4.9 kVA (4.4 kW) / 230V / 21.3A
PRP single-phase power *	4 kVA (3.6 kW) / 230V / 17.4A
Power factor (cos)	0.9
Battery charger	12V c.c
Insulation class	H

* Output power according to ISO 8528-1

Engine - Petrol, 4-Stroke, OHV, Natural Aspirated

Model	Honda GX 270
Output *	5.7 kW (7.7 HP)
Cylinders / Displacement	1 / 270cm ³
Speed	3000 rpm
Fuel consumption (75% of PRP)	1.6 l/h

* Power according to SAE J1349

General Specifications

Tank capacity	5.3 litres
Running time (75% Load)	3.3 hours
IP protection degree	IP 23
Dimensions LxWxH (mm)	650 x 520 x 490
Dry weight	56 Kg
Measured acoustic power LwA (pressure LpA)*	96 dB(A) (71 dB(A)
Guaranteed acoustic power LwA (pressure LpA)*	97 dB(A) (72 dB(A) @ 7m)

* Acoustic power according to European Directive 2000/14/EC



Optional

- Earthing kit
- Moving trolley CM8
- 230V/110V



Petrol Engine



Air Cooling



Manual Recoil



Sockets
230V

Order Code: 35.CJ8D7010