



P1PE P2000iLPG 1800W DUAL FUEL INVERTER GENERATOR

- 1800W Maximum output
- Compact, lightweight and portable
- Dual fuel, can be run on unleaded petrol or LPG
- ECO Mode, lowers engine RPM to increase fuel economy and lifespan
- Switch between petrol and LPG with ease
- Recoil Start
- 230V 3 Pin UK Plug, 12v DC & 5v USB Sockets
- Automatic low oil level shutdown to protect the engine

SPECIFICATION

Model	P2000iLPG
Engine Type	Hyundai 4 Stroke
Displacement	80cc
Rated Speed	4800rpm
Starting Method	Recoil
Fuel Type	Unleaded Petrol
Fuel Tank Capacity	4.5l
Fuel Consumption	
Oil Type	Semi-Synthetic 15W40
Oil Tank Capacity	350ml
Continuous Run Time	6h @ 50% load
Noise Level	63dB(A) @ 7m
Net Weight	21Kg

Sockets	1 x 230v 3 Pin UK Plug 1 x 12v DC 8 Amp 1 x 5v USB
Rated Output Power	1600w
Max Output Power	1800w
DC Output	12V / 5A
Frequency	50Hz
Accessories	Spark Plug Wrench Funnel

Rated Frequency	50Hz		
Rated Voltage	220V	230V	240V
Rated Current	4.0A	3.9A	3.75A