

PETROL GENERATOR 8500W



SC10000-II

PRODUCT FEATURES

- Electric start.
- Easy-to-start Senci single cylinder engine.
- Superior quality Senci alternator.
- AVR stabilizes the output power.
- Compact with open rugged durable frame.
- Wheel kit supplied for easy maneuverability.
- Super strong designed fuel tank.
- Circuit breaker cuts off electricity system when overloaded.
- Full closed control panel dustproof and water resistance.
- Low oil alert shuts down engine automatically.
- Unique muffler with spark arrestor, lower noise and more environmentally friendly.

PRODUCT INFO

RATED POWER	7.5 KW
MAXIMUM POWER	8.5 KW
SOCKETS	1 X 230 V 32 A 1 X 230 V 16 A
ENGINE	AP192FB (16 HP)
FUEL TYPE	PETROL
STARTING SYSTEM	ELECTRIC START
DISPLACEMENT	459 CC
FREQUENCY	50 HZ
FUEL CAPACITY	25 L
RUN TIME	6.5 HOURS @ 50% LOAD
NOISE LEVEL	65 DBA @ 7M
DIMENSIONS	720 X 556 X 580 MM
WEIGHT	98 KG



0845 505 3000



SENCI.CO.UK



INFO@SENCI.CO.UK