

## PETROL INVERTER GENERATOR 1.2kW



### FEATURES

- Powered by the latest EURO V emission standard, Senci 60cc recoil start petrol engine.
- Lightweight compact design, easy to carry.
- Advanced inverter technology for sensitive equipment.
- Indicator for output, low oil & overload alert.
- ECO mode to regulate the engine speed and adjust fuel consumption.
- Thermal breaker protects from overload.
- Fuel shut-off valve prevents carburettor contamination during storage.
- Automatic throttle for efficiency & lower noise output.
- Choke adjuster convenient for cold start.

### SPECIFICATIONS

PEAK OUTPUT	1200W
MAX. OUTPUT	1200W
CONTINUOUS OUTPUT	1100W
FUEL TYPE	Petrol
RUN TIME AT 50% LOAD	5h
OUTLETS	1 x 230V 13A, 1 x 12V 5A DC, 1 x 5V USB
FUEL TANK CAPACITY	2.6L
FREQUENCY	50Hz
LENGTH	465mm
WIDTH	285mm
HEIGHT	440mm
WEIGHT	12kg
NOISE LEVEL	59dB(A) @ 7m
STARTING METHOD	RECOIL
AVR (AUTOMATIC VOLTAGE REGULATOR)	N/A