

## FRAMED PETROL INVERTER GENERATOR 3.2kW



### FEATURES

- Powered by the latest EURO V emission standard, Senci AP170F petrol engine.
- Recoil start
- Advanced inverter technology for sensitive equipment.
- Indicator for output, low oil & overload alert.
- ECO mode to regulate the engine speed and adjust fuel consumption.
- Thermal breaker protects from overload.
- Reduced weight of 35kg for easier transport.
- Fuel shut-off valve prevents carburettor contamination during storage.

### SPECIFICATIONS

PEAK OUTPUT	3200W
MAX. OUTPUT	3200W
CONTINUOUS OUTPUT	3000W
FUEL TYPE	Petrol
RUN TIME AT 50% LOAD	11h
OUTLETS	2 x 230V 13A, 1 x 12V 8A DC
FUEL TANK CAPACITY	15L
FREQUENCY	50Hz
LENGTH	570mm
WIDTH	440mm
HEIGHT	480mm
WEIGHT	35kg
NOISE LEVEL	73dB(A) @ 7m
STARTING METHOD	RECOIL
AVR (AUTOMATIC VOLTAGE REGULATOR)	N/A