

### **18V RANDOM ORBIT** SANDER 5"

# **DBO180Z**

Model DB0180 has been developed as Makita's first cordless random orbit sanders powered by 18V Li-ion batteries. Features compact design with short height and lower center of gravity for better maneuverability. Ergonomically best possible grip design for comfortable handling. Excellent performance as powerful AC model gives high productivity.

18V RANDOM ORBIT SANDER 5"



### **TECHNICAL SPECIFICATIONS**

Battery Type

Body only machine

Voltage

Speed Control

Pad brake

Maximum Output

Orbits per Minute

**Orbit Diameter** 

Sanding Stroke per Minute

Paper Fastening

Pad Size Paper Size Vibration K factor Vibration: Sanding

Net weight

Lithium-ion

 $\sqrt{}$ 

18 v

3 stage push button

190 w

7000/9500/11000

opm

2.8 mm

14000/19000/

22000 spm

Hook & Loop

123 mm

125 mm

1.5 m/sec<sup>2</sup>

2.5 m/sec<sup>2</sup>

1.4 - 1.7 kg

#### **USER BENEFITS**

- Simple to operate electronic push button switch with 3-speed settings
- Fully Compatible with 18V 4.0Ah Battery with 36 minute charge time.
- Connectable to dust extractor
- Compact design with short height and lower centre of gravity for better manoeuvrability



Link to product - www.makitauk.com

# **RELATED PRODUCTS**

(Reco

OTHER